

**TPEXT\_ADDDB4POLLCB(3)**

REVISION HISTORY			
NUMBER	DATE	DESCRIPTION	NAME

# Contents

<a href="#">1</a>	<a href="#">SYNOPSIS</a>	<a href="#">1</a>
<a href="#">2</a>	<a href="#">DESCRIPTION</a>	<a href="#">2</a>
<a href="#">3</a>	<a href="#">RETURN VALUE</a>	<a href="#">3</a>
<a href="#">4</a>	<a href="#">ERRORS</a>	<a href="#">4</a>
<a href="#">5</a>	<a href="#">EXAMPLE</a>	<a href="#">5</a>
<a href="#">6</a>	<a href="#">BUGS</a>	<a href="#">6</a>
<a href="#">7</a>	<a href="#">SEE ALSO</a>	<a href="#">7</a>
<a href="#">8</a>	<a href="#">COPYING</a>	<a href="#">8</a>

## Chapter 1

# SYNOPSIS

```
#include <atmi.h>
```

```
int tpext_addb4pollcb(int (*p_b4pollcb)(void));
```

Link with *-latmisrv|-latmisrvnomain|-latmisrvinteg -latmi -lubf -lnstd -lpthread -lrt -lm*

---

## Chapter 2

# DESCRIPTION

Function registers callback function which is activated when XATMI server's main loop is going to poll for next message. The *p\_b4pollcb* callback function in case of success shall return 0. If *p\_b4pollcb* returns other value than 0, then XATMI server proceeds with shutdown.

This function is available only for XATMI servers.

---

## Chapter 3

# RETURN VALUE

On success, **tpext\_addb4pollcb()** return zero; on error, -1 is returned, with **tperrno** set to indicate the error.

## Chapter 4

# ERRORS

Note that **tpstrerror()** returns generic error message plus custom message with debug info from last function call.

**TPEINVAL** *p\_b4pollcb* paramter is NULL.

---

## Chapter 5

# EXAMPLE

See `atmitest/test008_extensions/atmisv.c` for sample code.



## Chapter 6

# BUGS

Report bugs to [madars.vitolins@gmail.com](mailto:madars.vitolins@gmail.com)

## Chapter 7

## SEE ALSO

`tpext_delb4pollcb(3)`

## Chapter 8

# COPYING

© Mavimax, Ltd