

TPSVRINIT(3)

REVISION HISTORY			
NUMBER	DATE	DESCRIPTION	NAME

Contents

1 SYNOPSIS	1
2 DESCRIPTION	2
3 RETURN VALUE	3
4 ERRORS	4
5 EXAMPLE	5
6 BUGS	6
7 SEE ALSO	7
8 COPYING	8

Chapter 1

SYNOPSIS

```
#include <atmi.h>
```

```
int tpsvrinit (int argc, char **argv);
```

For XATMI client link with *-latmiclt -latmi -lubf -lnstd -lpthread -lrt -lm*

For XATMI server link with *-latmisrv|-latmisrvnomain|-latmisrvinteg -latmi -lubf -lnstd -lpthread -lrt -lm*

Chapter 2

DESCRIPTION

This function is called upon server startup. Before the services are advertise, this function is activated. The *argc* and *argv* is command line paramters passed to binary after the *--*. Initial paramters are used by Enduro/X, these are sys-opts in the **ndrxconfig.xml**, after the *--* those are application specific options.

Normally at **tpsvrinit()** XATMI server does the **tpadvertise()**, and initialise other resources, like calling **tpopen()**. Any advertise done here, actually takes a part when function returns.

The function can be exposed to Enduro/X system in different ways:

1. If server binary is linked with *-latmisrv*, then server must contain public (non static) function of **tpsvrinit()**.
2. If server binary is linked with *-latmisrvnomain*, then above (1) rule still applies. But in this case the caller's **main()** must invoke **ndrx_main()** function.
3. If server binary is linked with *-latmisrvinteg*, then functions **tpsvrinit()** and **tpsvrdone()*** must be passed to **ndrx_main_integra()** function.

This only applies to XATMI servers.

Chapter 3

RETURN VALUE

If application failed to initialise, the user shall return non 0 value. If succeed, then 0 must be returned.

Chapter 4

ERRORS

Not available.

Chapter 5

EXAMPLE

See `atmitest/test001_basiccall/atmisv1.c` for sample code.

Chapter 6

BUGS

Report bugs to support@mavimax.com

Chapter 7

SEE ALSO

ndrx_main(3) **ndrx_main_integra(3)** **tpsvrinit(3)** **tpclose(3)** **tpopen(3)** **xadmin(8)**

Chapter 8

COPYING

© Mavimax, Ltd